

# SurMountor



**SUR-5050FRGB+IC30-5V**

FLEXIBLE STRIP introduction

Product specification


Lister: Lxlan

Assessor: 

Approver: 

## Features:

- The control signal will automatically transfer to the next led with SK6813 IC if one intermediate led is broken.
- All the good LEDs with SK6813 IC will work as normal except the one broken
- Each LED has a address IC and is programmable.
- High brightness & low power consumption.
- SPI LED strip with controller.
- Long life span LED lights, more than 50,000 hours+.
- Adhesive back, peel & stick!
- Operating temperature: -20~50°C.
- Non-waterproof, IP20.




## Applications:

Ideal for sign letters and channel letters, concealed lights, room lighting, equipment.

## Assembly drawing




### Top View




### Section



## Parameter:

SK6813, SPI LED strip, 30LED/Meter								
Part Number	Size	Color	Cut every (LEDS)	Inlay IC (5050)	Lumen/M	Voltage	Power/m	Packing/m
SUR-5050FRGB+IC30-5V	L5000*W10*H3	R 	1	SK6813	40.5	5V	6W	5Meters/reel
		G 			94.5			
		B 			20.25			


Radiation diagram




Relative luminous intensity Iv %

# LED Light distribution






for: red, blue, green, yellow



for: white LED

# How to connect flexible strip

Below shows you how to connect the flexible strip to power supplies.



## Package:



1 reel/bag



25 bags/Inner Box







50 Bags/Outer Box




Package: 5 meter strip in one reel, one reel in one anti-static bag, 25 bags put into one carton.

**! Cautions:**

When install the led strip, please note the installation technique. The led strip can be bent, but not distorted, as shown below:



**Distortion(Wrong)**



**Bend (Right)**